## logitech®



## DATA SHEET

# LOGITECH ROOMMATE

With computing power and video conferencing software together in a dedicated appliance, RoomMate makes it easy to deploy Zoom Rooms Appliances, Microsoft Teams Rooms on Android, and others with Logitech USB conferencecams like Rally and MeetUp.

# COMPUTING APPLIANCE PURPOSE-BUILT FOR VIDEO COLLABORATION

Bring the simplicity of video conferencing appliances to any meeting room with Logitech RoomMate. As a purpose-built appliance, RoomMate unites computing power and video conferencing software in a compact form factor. By connecting RoomMate to USB conferencecams like Logitech Rally Plus and up to two HD displays, IT can deploy Zoom Rooms Appliances, Microsoft Teams Rooms on Android, and other supported solutions in large to extra-large rooms. RoomMate is also compatible with Logitech MeetUp for small rooms.

RoomMate simplifies deployment without the need for a dedicated meeting room PC or Mac, and supports central monitoring and management through popular dashboards like Zoom Device Manager, Microsoft Teams Admin Center, and Logitech Sync.





In a sleek, low-profile form factor, Logitech RoomMate delivers all the power you need for HD video conferencing in rooms with one or two displays.



### **APPLIANCES GO LARGE**

In your small and medium rooms, the all-in-one Rally Bar Mini and Rally Bar appliances offer exceptionally easy setup and management. Now, you can bring that same convenience to your large meeting rooms by deploying RoomMate together with Rally Plus, Logitech's premium modular conference camera system for rooms with up to 46 seats.

### **SPECIFICATIONS**

| GENERAL   |  | INTERFACES   |   | SECURITY   |
|---|--|--|---|--|
| Appliance Mode: Supports compatible video conferencing software, including Zoom Rooms Appliances, Microsoft Teams Rooms on Android and additional video conferencing platforms.  Compatible Devices: Logitech MeetUp, Rally Camera, Rally System, Rally Plus System |  | HDMI Out: 2<br>HDMI In: 1<br>USB 3.0: 3x Type A<br>Network: 10/100/1G Ethernet<br>WiFi: 802.11a/b/g/n/ac (MIMO)  |   | Full Disk Encryption: AES-128  Data Encryption: Symmetric Keys, PKI  Device Identity: Protected by device attestation  Device Access: Authenticated using API  Key Protection: Arm TrustZone, RPMP  Device Security: Kensington Lock |
| DIMENSIONS  | PACKAGE CONTENTS   | POWER & CABLES   |   | ENVIRONMENTAL  |
| Height:<br>34.5 mm (1.36 in)<br>Width:<br>161 mm (6.34 itn)<br>Depth:<br>211 mm (8.31 in)   | Logitech RoomMate Power supply AC cable VESA bracket Remote control User documentation | Power Supply: Auto-sensing Operating Voltage/Power: 100-240V, 19V, 4.74A Power Supply Dimensions: 127mm x 51mm x 30mm DC Cable: 1.5m/4.9 ft AC Cable: 1m/3.28 ft |   | Operating Temperature: 0 to 40 °C  Storage Temperature: -40 to 70 °C  Humidity: 10 to 95%  |
| WARRANTY  |  |  |   | PART NUMBERS   |
| Standard: 2-year limited hardware warranty included  Extended: Additional one-year extended warranty available at the time of hardware purchase. Contact your reseller for availability.  |  |  | Logitech RoomMate: 950-000085 Extended Warranty: 994-000139 |  |

## logitech

www.logitech.com/roommate

Contact your reseller or contact us at www.logitech.com/vcsales

#### **Logitech Americas**

7700 Gateway Blvd. Newark, CA 94560 USA

#### Logitech Europe S.A.

EPFL - Quartier de l'Innovation Daniel Borel Innovation Center CH - 1015 Lausanne

**Logitech Asia Pacific Ltd.** Tel: 852-2821-5900 Fax: 852-2520-2230

© 2021 Logitech. Logitech, the Logitech logo and other Logitech marks are owned by Logitech and may be registered. All other trademarks are the properties of their respective owners. Logitech assumes no responsibility for any errors that may appear in this publication. Product, pricing and feature information contained herein is subject to change without notice.

Published January 2021